**Summary of Baseline and Residual Risks for Standard Industrial Hazards** 

	Risk Tables Description	Baseline Risk	Residual Risk
C.1	Non-Ionizing Radiation – Onsite-1 Facility Worker	R: I	R: III, IV
C.1	Non-Ionizing Radiation – Onsite-2 Co-located Worker	R: I	R: III, IV
C.1	Non-Ionizing Radiation – MOI Offsite	R: N/A	R: N/A
C.2	Toxic Materials – Onsite 1 Facility Worker	R: II	R: III, IV
C.2	Toxic Materials – Onsite 2 Co-located Worker	R: II	R: III, IV
C.2	Toxic Materials – MOI Offsite	R: II	R: III, IV
C.3	Flammable & Combustible Materials – Onsite-1 Facility Worker	R: I	R: IV
C.3	Flammable & Combustible Materials – Onsite-2 Co-located worker	R: II	R: IV
C.3	Flammable & Combustible Materials – MOI Offsite	R: III	R: IV
C.4	Electrical Energy – Onsite-1 Facility Worker	R: I	R: IV
C.4	Electrical Energy – Onsite-2 Co-located Worker	R: I	R: IV
C.4	Electrical Energy – MOI Offsite	R: I	R: IV
C.5	Thermal Energy – Onsite-1 Facility Worker	R: I	R: IV
C.5	Thermal Energy – Onsite-2 Co-located Worker	R: I	R: IV
C.5	Thermal Energy – MOI Offsite	R: III	R: IV
C.6	Kinetic Energy – Onsite-1 Facility Worker	R: I	R: III, IV
C.6	Kinetic Energy – Onsite-2 Co-located Worker	R: I	R: III, IV
C.6	Kinetic Energy – MOI Offsite	R: N/A	R: N/A
C.7	Potential Energy- Onsite-1 Facility Worker	R: I	R: III, IV
C.7	Potential Energy – Onsite-2 Co-located Worker	R: I	R: III, IV
C.7	Potential Energy – MOI Offsite	R: I	R: III
C.8	Magnetic Fields – Onsite-1 Facility Worker	R: I	R: III, IV
C.8	Magnetic Fields – Onsite-2 Co-located Worker	R: I	R: III, IV
C.8	Magnetic Fields – MOI Offsite	R: I	R: III, IV
C.9	Other Hazards – Onsite-1 Facility Worker	R: I	R: IV
C.9	Other Hazards – Onsite-2 Co-located Worker	R: I	R: IV
C.9	Other Hazards – MOI Offsite	R: I	R: IV
C.10	Access & Egress – Onsite-1 Facility Worker	R: I	R: IV
C.10	Access & Egress – Onsite-2 Co-located Worker	R: II	R: IV
C.10	Access & Egress – MOI Offsite	R: N/A	R: N/A
C.11	Environmental Hazards	R: I	R: IV

#### NOTE:

Per DOE-HDBK-1163-2020, Appendix C, "Risk Assessment Methodology": "Events with an unmitigated risk values of III or IV would not require additional control assignments to provide reasonable assurance of adequate protection. Whereas, for events with an unmitigated risk value of I or II, controls would need to be assigned to either reduce the likelihood or the consequence, and therefore the overall mitigated risk. Generally, preventive controls are applied prior to a loss event – reflecting a likelihood reduction and mitigative controls are applied after a loss event – reflecting a consequence reduction. Each control is credited for a single "bin drop" either in likelihood or consequence; not both. Following a standard hierarchy of controls, controls are applied until the residual risk is acceptable – reflecting a mitigated risk value of III or IV. After controls are credited, events with a remaining unacceptable residual risk (i.e., I or II) are candidates for additional analyses and additional controls, often quantitative in nature." For Fermilab, these controls for accelerator-specific hazards are identified as Credited Controls and further summarized in the Accelerator Safety Envelope (ASE).

#### C.1 Non-ionizing Radiation—Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Non-ionizing radiation-Laser	Hazard: Exposure to Class 3B and 4 lasers	L: A C: H R: I	P: Class 1 (light tight) enclosures P: ORC and work planning processes P: Locked/Interlocked system P: LOTO procedure or other procedure approved by the LSO P: Affected areas are posted M: Use of PPE	L: BEU C: M R: IV
	Exposure to Class 3R lasers	L: A C: L R: III	No analysis required	L: A C: L R: III
	Exposure to Class 1 and 2 Lasers	L: A C: N R: IV	No analysis required	L: A C: N R: IV
Non-ionizing radiation-RF	Hazard: Exposure from RF energy above allowed limits	L: A C: M R: II	P: RF Shielding P: ES&H periodic monitoring P: LOTO procedure P: Affected area postings	L: BEU C: M R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year	Co	onsequence (C, of	Risk (R, Qualitativ	e Ranking)	Risk Matrix					
A = Anticipated (L > 1.0E-02)	ev	ent)/year	<b>I</b> = situation (event)	<b>I</b> = situation (event) of major concern						
U = Unlikely (1.0E-02> L > 1.0E-04)	H	= High	II = situation (event	t) of concern						
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate	III = situation (ever	III = situation (event) of minor concern						
06)	L:	= Low	IV = situation (even)	IV = situation (event) of minimal concern				Lilza	lihood	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	N:	J = Negligible					A	U	EU	BEU
L)						Н	I	ī	II	III
Control(s) Type	С	Offsite (MOI) On	site-2 (co-located	Onsite-1 (facility worker)		п	1	1	11	111
<b>P</b> = Preventive (reduce event occurrence		wo	rker)			M	II	II	III	IV
likelihood)	H	$C \ge Irreversible,$	$C \ge Prompt worker$	$C \ge Prompt worker$	Consequences	L	III	III	IV	IV
<b>M</b> = Mitigative (reduces event consequences)		other serious effects, fat	, , ,							
Acronyms		or symptoms which	is immediately life-	that is immediately life-		N	IV	IV	IV	IV
<b>MOI</b> = Maximally-exposed Offsite Individual		could impair an	threatening or	threatening or						
		J 1	ermanently disabling.	permanently disabling.						
		take protective								
	_	action.								
	И	-	$C \ge Serious injury, no$	C ≥ Serious injury, no						
		adverse effects. in	nmediate loss of life no	immediate loss of life no						
		p	permanent disabilities;	permanent disabilities;						
		ho	ospitalization required.	hospitalization required.						
	L	Mild, transient	Minor injuries; no	Minor injuries; no						
		adverse effects > C	hospitalization > C	hospitalization > C						
	V	Consequences less C	Consequences less than	Consequences less than						
		than those for Low	those for Low	those for Low						
		Consequence Level	Consequence Level	Consequence Level						

#### Non-ionizing Radiation - Onsite-2 Co-located Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Non-ionizing radiation-Laser	Hazard: Exposure to Class 3B and 4 lasers	L: A C: H R: I	P: Class 1 (light tight) enclosures P: Locked/Interlocked system or administrative control approved by the LSO P: LOTO procedure or other procedure approved by the LSO P: Affected areas are posted	L: BEU C: H R: IV
	Exposure to Class 3R lasers	L: A C: L R: III	No analysis required	L: A C: L R: III
	Exposure to Class 1 and 2 Lasers	L: A C: N R: IV	No analysis required	L: A C: N R: IV
Non-ionizing radiation-RF	Hazard: Exposure from RF energy above allowed limits	L: A C: M R: II	P: RF Shielding P: ES&H periodic monitoring P: LOTO procedure performed by facility worker P: Affected area postings	L: BEU C: M R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	event)/year		I = situation (event) II = situation (event) III = situation (event)	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern					lihood	
L)						Н	A	U	EU II	BEU
Control(s) Type P = Preventive (reduce event occurrence	С		nsite-2 (co-located orker)	Onsite-1 (facility worker)		M	II	П	III	IV
likelihood) <b>M</b> = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects, fa	$C \ge Prompt worker$ stality or acute injury that	C ≥ Prompt worker at fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which	is immediately life- threatening or	that is immediately life- threatening or		N	IV	IV	IV	IV
WOI – Maximany-exposed Offsite individual	1		permanently disabling.	permanently disabling.						
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; aspitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
		Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	N	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level						

#### Non-ionizing Radiation – MOI Offsite

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Non-ionizing	Hazard: N/A	L:		L:
Radiation-		C:		C:
Laser		R:		R:
Non-ionizing	Hazard: N/A	L:		L:
Radiation-RF		C:		C:
		R:		R:

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year	Co	nsequence (C, of	Risk (R, Qualitati	ve Ranking)	Risk Matrix					
A = Anticipated (L > 1.0E-02)	eve	ent)/year	I = situation (event	<b>I</b> = situation (event) of major concern						
U = Unlikely (1.0E-02 > L > 1.0E-04)	H :	= High	II = situation (ever	II = situation (event) of concern						
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate	III = situation (eve	ent) of minor concern						
06)	L=	= Low	IV = situation (eve	nt) of minimal concern				Like	lihood	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	<b>N</b> =	= Negligible		, , ,			A	U	EU	BEU
L)						Н	T	I	II	III
Control(s) Type	C	0 ( 0 -)	,	Onsite-1 (facility worker)			1	1		
<b>P</b> = Preventive (reduce event occurrence	<u> </u>		worker)			M	II	II	III	IV
likelihood)	H	$C \ge Irreversible$ ,	$C \ge Prompt worker$	$C \ge Prompt worker$	Consequences	L	III	III	IV	IV
<b>M</b> = Mitigative (reduces event consequences)		other serious effects,	fatality or acute injury	fatality or acute injury		L				
Acronyms				that is immediately life-		N	IV	IV	IV	IV
<b>MOI</b> = Maximally-exposed Offsite Individual		could impair an	threatening or	threatening or						
		individual's ability	permanently disabling.	permanently disabling.						
		to take protective								
		action.								
	M	$C \ge Mild$ , transient	C ≥ Serious injury, no	$C \ge$ Serious injury, no						
		adverse effects.	immediate loss of life no	immediate loss of life no						
			permanent disabilities;	permanent disabilities;						
			hospitalization required.	hospitalization						
				required.						
	L	Mild, transient	Minor injuries; no	Minor injuries; no						
		adverse effects > C	hospitalization > C	hospitalization > C						
	N	Consequences less	Consequences less than	Consequences less than						
		than those for Low	those for Low	those for Low						
		Consequence Level	Consequence Level	Consequence Level						

#### C.2 Toxic Materials – Onsite 1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Lead	lead bricks, lead shot, lead sheets, lead paint, and soldering operations.	L: A C: M R: II	P: Administrative policy (moving 10 bricks per day per FESHM) P: Lead handling training M: PPE (dermal and respiratory) M: IH Sampling (vertical standard)	L: EU C: N R: IV
Beryllium	Reference: FESHM, Chapter XXXX  Hazard: Potential exposure to beryllium dust during manual handling of un-encased activities (including clean-up).  Reference: FESHM, Chapter XXXY	L: A C:M R: II	P: Administrative policy (ESH review required per FESHM, permitting, etc.) P: Training (Three current beryllium trainings maintained at Fermilab) M: IH Sampling (vertical standard) M: PPE (dermal and respiratory)	L: EU C: L R: IV
Fluorinert & Its byproducts	Hazard:  • Potential exposure to fFluorinert	L: U C: N R: IV	Evaluated as non-hazardous through pattern of use	L: U C: N R: IV
	Potential exposure to Fluorinert decomposition products (HF, PFIB).  Reference: SDS-HF, and PFIB		P: Fluorinert and decomposition products are contained in a closed system M: Filtration installed to remove hazardous byproducts and reduces consequence of exposure	L: EU C: M R: III
Liquid Scintillator Oil	Hazard:  • Airborne exposure via outgassing oil  Reference: NOvA scintillator oil	L: A C: L R: III	P: Secondary containment prevents contact if leakage occurs P: WPC program reviews this hazard to prevent potential exposure during handling M: Administrative control (perform the work with sufficient ventilation) M: PPE during filling and draining evolutions	L: EU C: N R: IV
Ammonia	Hazard:  • Exposure to target material	L: A C: M R: II	P: Standard Operating Procedures for handling M: PPE (dermal) M: Engineering control (Room ventilation)	L: U C: M R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Nanoparticle	Hazard:	L: A	P: ESH review (work planning, Hazard Analysis, SOP, etc.)	L: EU
Exposures	Airborne exposure	C: L	P: Administrative controls (training)	C: L
		R: III		R: IV

Chemical Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year	Co	nsequence (C, of		Risk (R, Qualitative Ranking)		Risk Matrix					
A = Anticipated (L > 1.0E-02)	eve	ent)/year		I = situation (event) of major concern					Like	lihood	
U = Unlikely (1.0E-02 > L > 1.0E-04)	H :	= High		II = situation (even			Α	U	EU	BEU	
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate		<b>III</b> = situation (eve	nt) of minor concern		Н	I	I	II	III
06)	L =	= Low <b>IV</b> = situation (event) of minimal concern				M	ш	II	III	IV	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	N=	= Negligible			Consequences	1V1	11	- 11	111	1 V	
L)					_	Consequences	L	III	III	IV	IV
Control(s) Type	С	( - )		-2 (co-located	Onsite-1 (facility worker)		N	IV	IV	IV	IV
<b>P</b> = Preventive (reduce event occurrence			worke	r)			11	1 V	1 V	1 V	1 V
likelihood)	H	C ≥ PAC-2		$C \ge PAC-3$	C ≥ IDLH						
<b>M</b> = Mitigative (reduces event consequences)	И	$PAC-2 > C \ge PAC-1$	PAC	$C-3 > C \ge PAC-2$	$IDLH > C \ge PEL$ or						
Acronyms					$TLV_c$						
<b>IDLH</b> = Immediately Dangerous to Life and	L	PAC-1 > C		PAC-2 > C	PEL or $TLV_c > C$						
Health	N	Consequences less	Cons	equences less than	Consequences less than						
<b>MOI</b> = Maximally-exposed Offsite Individual		than those for Low	1	those for Low	those for Low						
<b>PAC</b> = Protective Action Criteria		Consequence Level	Coı	nsequence Level	Consequence Level						
<b>PEL</b> = Permissible Exposure Limit		•		•	•						
$TLV_c$ = Threshold Limit Value (ceiling)											

#### **Toxic Materials – Onsite 2 Co-located Worker**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Lead	Hazard: Potential exposure to lead during manual handling of un-encased lead bricks, lead shot, lead sheets, lead paint, and soldering operations.  Reference: FESHM		P: Work practice control (preventing access to area, prohibiting food and drink, etc.) P: Barriers established for lead work	L: EU C: L R: IV
Beryllium *	Hazard:  • Potential exposure to beryllium dust for personnel in the vicinity of manual handling of un-encased material.  Reference: FESHM	L: U C: H R: II	P: Work planning (ESH oversite, i.e. Fermilab doesn't typically allow machining beryllium in general) P: Work practice control (preventing access to area, prohibiting food and drink, etc.) P: Beryllium work signage	L: BEU C: H R: III
Fluorinert & Its byproducts	Hazard:  • Potential exposure to fluorinert  • Potential exposure to	R: IV	Evaluated as non-hazardous through pattern of use  P: Fluorinert and decomposition products are contained in a closed system  M: Filtration installed to remove hazardous byproducts and reduces consequence of exposure	L: U C: N R: IV L: EU C: L R: IV
Liquid Scintillator Oil	Reference: SDS-HF, and PFIB  Hazard:  • Airborne exposure via outgassing oil  Reference: NOvA scintillator oil	L: A C: N R: IV	No further analysis required	L: A C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Ammonia	Hazard:  • Exposure to target material	L: A C: L R: III	M: Engineering control (room ventilation)	L: A C: N R: IV
Nanoparticle Exposures	Hazard:  • Airborne exposure	L: A C: N R: IV	No further analysis required	L: A C: N R: IV

Chemical Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year	Co	nsequence (C, of		Risk (R, Qualitati	ve Ranking)	Risk Matrix					
A = Anticipated (L > 1.0E-02)	eve	ent)/year		I = situation (event) of major concern				Likelihood			
U = Unlikely (1.0E-02 > L > 1.0E-04)	Η:				II = situation (event) of concern			A	U	EU	BEU
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate			nt) of minor concern		Н	I	I	II	III
06)	L =	= Low			nt) of minimal concern		M	II	II	III	IV
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	N=	= Negligible	ligible			Consequences	171	11	11	111	1 V
L)						Somsequences	L	III	III	IV	IV
Control(s) Type	С	( )		-2 (co-located	Onsite-1 (facility worker)		N	IV	IV	IV	IV
<b>P</b> = Preventive (reduce event occurrence	<u> </u>		workei	<u>r)</u>			11	1 V	1 V	1 V	1 V
likelihood)	H	C ≥ PAC-2		$C \ge PAC-3$	C ≥ IDLH						
<b>M</b> = Mitigative (reduces event consequences)	И	$PAC-2 > C \ge PAC-1$	PAC	$C-3 > C \ge PAC-2$	$IDLH > C \ge PEL$ or						
Acronyms					$TLV_c$						
<b>IDLH</b> = Immediately Dangerous to Life and	L	PAC-1 > <b>C</b>		PAC-2 > C	PEL or $TLV_c > C$						
Health	N	Consequences less	Cons	sequences less than	Consequences less than						
<b>MOI</b> = Maximally-exposed Offsite Individual		than those for Low	1	those for Low	those for Low						
<b>PAC</b> = Protective Action Criteria		Consequence Level	Cor	nsequence Level	Consequence Level						
<b>PEL</b> = Permissible Exposure Limit				•							
TLV <sub>c</sub> = Threshold Limit Value (ceiling)											

#### **Toxic Materials – MOI Offsite**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Lead	Hazard: Potential exposure to unencased lead bricks, lead shot, lead sheets, and lead paint waste.  Reference: FESHM	L: EU C: M R: III	P: Access prevention (facility doors are typically locked)	L: BEU C: M R: IV
Beryllium	Hazard:  • Potential exposure to beryllium.  Reference: FESHM	L: EU C: H R: II	P: Access prevention (facility doors are typically locked)	L: BEU C: H R: III
Fluorinert & Its byproducts	Hazard:  • Potential exposure to fluorinert	L: EU C: N R: IV	Evaluated as non-hazardous through pattern of use	L: U C: N R: IV
	F ( )-	L: EU C: H R : II	P: Access to the public is prevented M: Filtration installed to remove hazardous byproducts and reduces consequence of exposure	L: BEU C: M R: IV
Liquid Scintillator Oil	Reference: SDS-HF, and PFIB  Hazard: Airborne exposure via outgassing oil	L: EU C: N R: IV	Further analysis not required	L: EU C: N R: IV
Ammonia	Hazard: Exposure to target material	L: EU C: N R: IV	Further analysis not required	L: EU C: N R: IV
Nanoparticle Exposures	Hazard: Airborne exposure	L: EU C: N R: IV	Further analysis not required	L: EU C: N R: IV

Chemical Hazard Consequences, derived fro	m I	Figure C-1, "Example	Quali	itative Consequenc	e Matrix", DOE-HDBK	-1163-2020.					
Likelihood (L, of event)/year	Co	nsequence (C, of		Risk (R, Qualitativ	ve Ranking)	Risk Matrix					
A = Anticipated (L > 1.0E-02)	eve	ent)/year		I = situation (event)	= situation (event) of major concern			Likelihood			
U = Unlikely (1.0E-02 > L > 1.0E-04)	Η:	= High			II = situation (event) of concern			Α	U	EU	BEU
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate			<b>III</b> = situation (event) of minor concern		Н	I	I	II	III
06)	L :	= Low				M	II	II	III	IV	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	<b>N</b> :	= Negligible	rligible		Consequences	1V1	11	11	111	1 V	
L)					Consequences	L	III	III	IV	IV	
Control(s) Type	C	Offsite (MOI)	Onsite-	-2 (co-located	Onsite-1 (facility worker)		N	IV	IV	IV	IV
<b>P</b> = Preventive (reduce event occurrence			worke	r)			IN	1 V	1 V	1 V	1 V
likelihood)	Η	$C \ge PAC-2$		$C \ge PAC-3$	$C \ge IDLH$						
<b>M</b> = Mitigative (reduces event consequences)	И	$PAC-2 > C \ge PAC-1$	PAC	$C-3 > C \ge PAC-2$	$IDLH > C \ge PEL$ or						
Acronyms					$TLV_{c}$						
<b>IDLH</b> = Immediately Dangerous to Life and	L	PAC-1 > C		PAC-2 > C	PEL or $TLV_c > C$						
Health	V	Consequences less	Cons	sequences less than	Consequences less than						
<b>MOI</b> = Maximally-exposed Offsite Individual		than those for Low	1	those for Low	those for Low						
<b>PAC</b> = Protective Action Criteria		Consequence Level	Coı	nsequence Level	Consequence Level						
<b>PEL</b> = Permissible Exposure Limit		_ ^		•	*						
TLV <sub>c</sub> = Threshold Limit Value (ceiling)											

#### C.3 Flammable and Combustible Materials – Onsite -1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Combustible materials (cables, boxes, paper, wood cribbing, etc.)	Hazard: This hazard is a potential facility fire. The presence of excessive combustible materials can pose a hazard stemming from inadequate housekeeping practices. This hazard can add to the fuel load of a potential facility fire. Poor housekeeping can also lead to life safety concerns, such as egress obstructions and tripping hazards. The exposure of the hazard to the facility worker is of major concern. Reference: FESHM Chapter 2005 Operational Readiness Clearance & 6010 Fire Protection Program	C: H R: I	P: The use of Operational Readiness Clearance (ORC) and/or WPC process determine if additional combustibles will be introduced to the area P: Fire Safety and Life Safety Inspections are performed by the Fire Protection Group and the Fire Department P: Fire alarm systems ITM is performed at prescribed frequencies P: Prior to restart, a walkdown is conducted of the complex verifying transient combustibles are removed before operational activities commence P: Hot work program administered by the Fire Department M: Smoke, heat, sprinklers, are monitored by a sitewide monitoring system with notification to the emergency dispatch center that is constantly staffed, 24/7, 365 days M: Fire detection and/or suppression is present M: Manual fire suppression services are provided, i.e., fire hydrants, throughout the complex M: Egress stairways are constructed as fire barriers M: On-site fire department trained in radiological environments	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
	Hazard:  The presence of flammable gases in cylinders or storage containers pose an inherent hazard due to their flammability/combustibility properties.  Exposure to hot work provides a dangerous situation where flammable liquids will ignite. Unmitigated this could lead to an explosion and subsequent fire.  The exposure of the hazard to the facility worker is of major concern.  Reference: FESHM Chapters 2005 Operational Readiness Clearance, 6010 Fire Protection Program, 6020.3 Flammable Gases, 6020.4, Combustible & Flammable Liquids	C: H R: I	and/or WPC process determine if additional	L: BEU C: N R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L >1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L >1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU	
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III	
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### Flammable and Combustible Materials – Onsite -2 Co-located Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Combustible materials (cables, Boxes, Paper, wood cribbing, etc.)		C: M R: II	and/or WPC process determine if additional	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Materials (Flammable gas, cleaning materials, etc.)	Hazard: The presence of flammable gases in cylinders or storage containers pose an inherent hazard due to their flammability/combustibility properties.  Exposure to hot work provides a dangerous situation where flammable liquids will ignite. Unmitigated this could lead to an explosion and subsequent fire.  The exposure of the hazard to the co-located worker is of concern.  Reference: FESHM Chapters 2005 Operational Readiness Clearance, 6010 Fire Protection Program, 6020.3 Flammable Gases, 6020.4, Combustible & Flammable Liquids 4	C: M R: II	and/or WPC process determine if additional	L: BEU C: N R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L >1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L >1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU	
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III	
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### Flammable and Combustible Materials – MOI Offsite

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
materials (cables, Boxes, Paper, wood cribbing, etc.)		C: L R: III	Fermilab restricts public access to accelerator complex	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Materials (Flammable gas, cleaning materials, etc.)	Hazard: The presence of flammable gases in cylinders or storage containers pose an inherent hazard due to their flammability/combustibility properties.  Exposure to hot work provides a dangerous situation where flammable liquids will ignite. Unmitigated this could lead to an explosion and subsequent fire.  The exposure of the hazard to the public is of minor concern.  Reference: FESHM Chapters 2005 Operational Readiness Clearance, 6010 Fire Protection Program, 6020.3 Flammable Gases, 6020.4, Combustible & Flammable Liquids	C: L R: III	Fermilab restricts public access to accelerator complex	L: BEU C: N R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H = M L =	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (eve II = situation (ev III = situation (ev	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	elihood EU	BEU	
L) Control(s) Type	С	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III	
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	II	II	III	IV	
likelihood) <b>M</b> = Mitigative (reduces event consequences)	Н	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms		or symptoms which t	that is immediately life	- that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling	threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life n permanent disabilities nospitalization required	o immediate loss of life no permanent disabilities;							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	N	Consequences less than those for Low Consequence Level	Consequences less that those for Low Consequence Level	•							

#### C.4 Electrical Energy – Onsite-1 Facility Worker

Hazard	Hazard	Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Stored Energy Exposure	inte enc • inte	Shock hazard, 50 V, Non- erlocked closures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / LOTO Procedures / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit magnet power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation	L: BEU C: L R: IV L: BEU C: L R: IV
Stored Energy Exposure	enc	Shock hazard,>50 Interlocked closure area Arc Flash, terlocked enclosure	R: I L: A C: H	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access OR Electrical Safety System turns off systems with exposed conductors when key issued P: Access to enclosure requires key issued for specific, daily access P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / LOTO Procedures / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit magnet power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation M: Passive dissipation of stored energy for magnet power supplies	L: BEU C: N R: IV L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
High Voltage Exposure	Hazard:  • Shock hazard, voltage > 50 V, Noninterlocked enclosures  • Arc Flash, Noninterlocked enclosures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / LOTO Procedures / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation	L: BEU C: L R: IV L: BEU C: L R: IV
High Voltage Exposure	Hazard: Shock hazard, voltage > 50 V, Interlocked enclosures  • Arc Flash, Interlocked enclosures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access OR Electrical Safety System turns off systems with exposed conductors when key issued. P: Access to enclosure requires key issued for specific, daily access P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / LOTO Procedures / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation	L: BEU C: L R: IV L: BEU C: L R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Low Voltage,	Hazard:	L: U	P: Equipment is enclosed, and tool use or lock removal is required to	L: BEU
High Current	• Arc Flash, Non-	C: H	access	C: L
Exposure.	interlocked enclosures		P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / LOTO Procedures / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation.	R: IV
		L: U		L: BEU
	<ul> <li>Fire hazard from high current causing smoke inhalation and burns.</li> </ul>	R: I	P: Equipment is enclosed preventing fire initiation. P: Overcurrent protection devices are designed into equipment. P: Ground current monitors inhibit power supply operation when excessive ground current is detected. M: Combustible controls mitigate potential fire initiation. M: Smoke detectors mitigate potential personnel exposure to smoke inhalation.	C: L R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Low Voltage, High Current Exposure.	Hazard: • Arc Flash, Interlocked enclosures	C: H R: I	P: Equipment is enclosed, and tool use or lock removal is required to access OR Electrical Safety System turns off systems with exposed conductors when key issued. P: Access to enclosure requires key issued for specific, daily access P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / LOTO Procedures / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation.	L: BEU C: L R: IV
	• Fire hazard from high current causing smoke inhalation and burns.	C: H R: I	P: Equipment is enclosed preventing fire initiation. P: Overcurrent protection devices are designed into equipment. P: Ground current monitors inhibit power supply operation when excessive ground current is detected. M: Combustible controls mitigate potential fire initiation. M: Fire detectors mitigate potential personnel exposure to smoke inhalation.	L: BEU C: L R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year	Co	nsequence (C, of	Risk (R, Qualitati	ve Ranking)	Risk Matrix					
A = Anticipated (L > 1.0E-02)	eve	ent)/year	<b>I</b> = situation (event)	I = situation (event) of major concern						
U = Unlikely (1.0E-02> L > 1.0E-04)		= High	$\mathbf{H} = \text{situation (even)}$	II = situation (event) of concern						
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate	<b>III</b> = situation (ever	nt) of minor concern						
06)	L:	= Low	IV = situation (even	nt) of minimal concern				Like	lihood	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	N:	= Negligible					A	U	EU	BEU
L)						Н	ĭ	ī	II	III
Control(s) Type	С	( - )	`	Onsite-1 (facility worker)			1	1		
<b>P</b> = Preventive (reduce event occurrence	L		vorker)			M	II	II	III	IV
likelihood)	Н	$C \ge Irreversible,$	$C \ge Prompt worker$	$C \ge Prompt worker$	Consequences	L	III	III	IV	IV
<b>M</b> = Mitigative (reduces event consequences)		other serious effects,	fatality or acute injury	fatality or acute injury						
Acronyms		or symptoms which	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV
<b>MOI</b> = Maximally-exposed Offsite Individual		could impair an	threatening or	threatening or						
		-	permanently disabling.	permanently disabling.						
		take protective								
	_	action.	a. a. l. l.	a. a						
	VI	$C \ge Mild$ , transient	$C \ge Serious injury, no$	C ≥ Serious injury, no						
		adverse effects.		immediate loss of life no						
			permanent disabilities;	permanent disabilities;						
				hospitalization required.						
	L	Mild, transient	Minor injuries; no	Minor injuries; no						
		adverse effects > C	hospitalization > C	hospitalization > C						
	N	Consequences less	Consequences less than	Consequences less than						
		than those for Low	those for Low	those for Low						
		Consequence Level	Consequence Level	Consequence Level						

#### **Electrical Energy Onsite-2 Co-located Worker**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)	
Stored Energy Exposure	Hazard:  • Shock hazard, >50 V, Non- interlocked enclosures  • Arc Flash, Non- interlocked enclosures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access P: Building access restricted to trained individuals P: Basic electrical training for all workers M: Ground current monitors inhibit magnet power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation.	L: BEU C: M R: IV L: BEU C: M R: IV	
Stored Energy Exposure	Hazard:  • Shock hazard, >50 V, Interlocked enclosures  • Arc Flash, Interlocked enclosures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access OR Electrical Safety System turns off systems with exposed conductors when key issued P: Building access restricted to trained individuals P: Access to enclosure requires key issued for specific, daily access P: Basic electrical training for all workers M: Ground current monitors inhibit magnet power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation. M: Passive dissipation of stored energy for magnet power supplies	L: BEU C: L R: IV L: BEU C: L R: IV	
High Voltage Exposure	Hazard: Shock hazard, voltage > 50 V, Non-interlocked enclosures  • Arc Flash, Non- interlocked enclosures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels), and tool use or lock removal is required to access P: Building access restricted to trained individuals P: Basic electrical training for all workers M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation	L: BEU C: M R: IV L: BEU C: M R: IV	

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
High Voltage Exposure	Hazard: Shock hazard, voltage > 50 V, Interlocked enclosures  • Arc Flash, Interlocked enclosures	L: A C: H R: I L: A C: H R: I	P: Equipment is enclosed (dead front panels) and tool use or lock removal is required to access OR Electrical Safety System turns off systems with exposed conductors when key issued. P: Building access restricted to trained individuals P: Access to enclosure requires key issued for specific, daily access P: Basic electrical training for all workers M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation	L: BEU C:M R: IV L: BEU C: M R: IV
Low Voltage, High Current Exposure.	• Arc Flash Non- interlocked enclosures  • Fire hazard from high current causing smoke inhalation and burns service building areas.	L: U C: H R: I L: U C: H R: I	P: Equipment is enclosed, and tool use or lock removal is required to access P: Training for electrical workers including no energized manipulative work policy P: Hazard Analysis / Standard Operating Procedures for work on electrical equipment M: Personnel protective equipment and training in proper use. M: Ground current monitors inhibit power supply operation when excessive ground current is detected. Intended for equipment protection but provides some shock mitigation P: Equipment is enclosed preventing fire initiation. P: Overcurrent protection devices are designed into equipment. P: Ground current monitors inhibit power supply operation when excessive ground current is detected. M: Combustible controls mitigate potential fire initiation. M: Smoke detectors mitigate potential personnel exposure to smoke inhalation.	L: BEU C: L R: IV L: BEU C: L R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Low Voltage, High Current Exposure.	Hazard: • Arc Flash, Interlocked enclosures	L: U C: H R: I	access OR Electrical Safety System turns off systems with exposed	L: BEU C: M R: IV
	• Fire hazard from high current causing smoke inhalation and burns, beam line enclosure areas	L: U C: H R: I	P: Equipment is enclosed preventing fire initiation. P: Overcurrent protection devices are designed into equipment. P: Ground current monitors inhibit power supply operation when excessive ground current is detected.	L: BEU C: L R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H = M L =	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (eve II = situation (ev III = situation (ev	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	elihood EU	BEU
L) Control(s) Type	С	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	II	II	III	IV
likelihood) <b>M</b> = Mitigative (reduces event consequences)	Н	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which t	that is immediately life	- that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling	threatening or permanently disabling.						
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life n permanent disabilities nospitalization required	o immediate loss of life no permanent disabilities;						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	N	Consequences less than those for Low Consequence Level	Consequences less that those for Low Consequence Level	•						

#### **Electrical Energy – MOI Offsite**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Stored Energy	Hazard: Shock hazard, >50 V,	L: A	P: Equipment is enclosed (dead front panels), and tool use is required	L: BEU
Exposure	Arc flash	C: H	for access	C: M
1		R: I		R: IV
			P: Lock removal is required to access	
			M: Passive dissipation of stored energy for magnet power supplies	
High Voltage	Hazard: Shock hazard, >50 V,	L: A	P: Equipment is enclosed (dead front panels), and tool use id required	L: BEU
Exposure	Arc flash outside	C: H	for access	C: M
•		R: I		R: IV
			P: Lock removal is required to access	
			M: Ground current monitors inhibit power supply operation when	
	Deference		excessive ground current is detected. Intended for equipment	
	Reference:		protection but provides some shock mitigation	
Low Voltage,	Hazard: N/A	L:	Public does not have access to this hazard	L:
High Current		C:		C:
Exposure.		R:		R:

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02) U = Unlikely (1.0E-02> L > 1.0E-04) EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06) BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	elihood EU	BEU
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III
<b>P</b> = Preventive (reduce event occurrence		w	orker)		Conseguences	M	II	П	III	IV
likelihood) <b>M</b> = Mitigative (reduces event consequences)	н	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.						
	И		C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	V	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level						

#### C.5 Thermal Energy – Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Bakeout	Hazard:  A bakeout will cause elevated temperatures.  Hotter than 100 C (212 F) degrees for 4-5 days.  If the bake out were to not have runaway temperature capabilities, this could lead to excessive heat and burning, which could potentially lead to a fire.  The presence of excessive combustible materials can pose a hazard stemming from inadequate housekeeping practices.  This hazard can add to the fuel load of a potential fire.  The exposure of the hazard to the facility worker is of major concern.  Reference: FESHM Chapter 6020.2 Hot Work Program		restricted, and transient combustibles have been	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Hot Work			nersonnel and they must meet all the requirements of the	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Cryogenics	Hazard:  Cryogenics are inherently a low risk on their own as they are non-flammable and non-toxic.  However, if exposed to the cryogenic liquids, they have the potential of burning skin and creating an oxygen deficient atmosphere which can lead to death.  The exposure of the hazard to the facility worker is of major concern.  Reference: FESHM 4240 ODH, 5032 Cryogenics System Review, 5032.1 Liquid Nitrogen Dewar Installation and Operation Rules, 5032.2 Liquid Cryogenic Targets	Burns L: A C: H R: I	P: Personnel must be medically qualified to enter ODH spaces. P: Portable Oxygen Monitoring is provided for ODH spaces in accordance with the WPC P: Fire Safety and Life Safety Inspections are performed Fire Protection Group and the Fire Department. P: ODH alarm systems are tested and maintained M: ODH alarms are monitored by a sitewide monitoring system with notification to the emergency dispatch center that is constantly staffed, 24/7, 365 days. M: Area/fixed Oxygen Monitoring provided in areas where cryogenic liquids are stored M: Onsite Emergency services are provided. P: Cryogenic system designed and reviewed by qualified personnel P: WPC process provides instructions for use P: Protective clothing rules are enforced when working in areas with exposure to cryogenic liquids. P: Training required for all personnel handling cryogenics M: Onsite Emergency services are provided	ODH L: BEU C: N R: IV  Burns L: BEU C: M R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern			A	Like U	elihood EU	BEU
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III
<b>P</b> = Preventive (reduce event occurrence		w	orker)		Conseguences	M	II	П	III	IV
likelihood) <b>M</b> = Mitigative (reduces event consequences)	н	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.						
	И		C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	V	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level						

#### Thermal Energy – Onsite-2 Co-located Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Bakeout	Hazard:  A bakeout will cause elevated temperatures. If the bake out were to not have runaway temperature capabilities, this could lead to excessive heat and burning, which could potentially lead to a fire.  The presence of excessive combustible materials can pose a hazard stemming from inadequate housekeeping practices.  This hazard can add to the fuel load of a potential fire.  The exposure of the hazard to the co-located worker is of minor concern.  Reference: FESHM Chapter 6020.2 Hot Work Program		restricted, and transient combustibles have been	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Hot Work	Hazard:  Hot work will cause elevated temperatures. If hot work is not supervised, there is a potential for combustibles in the surrounding area to be ignited due to exposure to slag or elevated temperatures. This could lead to excessive heat and burning, which could potentially lead to a fire.  The presence of excessive combustible materials can pose a hazard stemming from inadequate housekeeping practices.  This hazard can add to the fuel load of a potential fire.  The exposure of the hazard to the co-located worker is of minor concern.  Reference: FESHM Chapter 6020.2		nersonnel and they must meet all the requirements of the	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Cryogenic Liquids	helium and nitrogen are inherently a low risk on their own as they are non-flammable and non-toxic.  However, if exposed to the cryogenic liquids, they have the potential of burning skin and creating an oxygen deficient atmosphere which can lead to death.  The exposure of the hazard to the	ODH L: A C:H R: I  Burns L: A C: H R: I	P: Personnel must be medically qualified to enter ODH spaces. P: Portable Oxygen Monitoring is provided for ODH spaces in accordance with the WPC P: Fire Safety and Life Safety Inspections are performed Fire Protection Group and the Fire Department. P: ODH alarm systems are tested and maintained M: ODH alarms are monitored by a sitewide monitoring system with notification to the emergency dispatch center that is constantly staffed, 24/7, 365 days. M: Area/fixed Oxygen Monitoring provided in areas where cryogenic liquids are stored M: Onsite Emergency services are provided. P: Cryogenic system designed and reviewed by qualified personnel P: WPC process provides instructions for use P: Protective clothing rules are enforced when working in areas with exposure to cryogenic liquids. P: Training required for all personnel handling cryogenics M: Onsite Emergency services are provided	ODH L: BEU C: N R: IV  Burns L: BEU C:M R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.						
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level						

#### Thermal Energy – MOI Offsite

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Bakeout	Hazard: N/A  A bakeout will cause elevated temperatures. If the bake out were to not have runaway temperature capabilities, this could lead to excessive heat and burning, which could potentially lead to a fire.  The presence of excessive combustible materials can pose a hazard stemming from inadequate housekeeping practices.  This hazard can add to the fuel load of a potential fire.  The exposure of the hazard to the public is of minimal concern.  Reference: FESHM 6020.2			L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Hot Work	Hot work will cause elevated temperatures. If hot work is not supervised, there is a potential for combustibles in the surrounding area to be ignited due to exposure to slag or elevated temperatures. This could lead to excessive heat and burning, which could potentially lead to a fire.  The presence of excessive combustible materials can pose a hazard stemming from inadequate housekeeping practices.  This hazard can add to the fuel load of a potential fire.  The exposure of the hazard to the public is of minimal concern.  Reference: FESHM 6020.2		HESHLICIS DIDDIC ACCESS TO ACCEDEDATOL CONTINEX	L: BEU C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Cryogenic Liquids	Hazard: Burns from contact  Cryogenic liquids, such as liquid helium and nitrogen are inherently a low risk on their own as they are non-flammable and non-toxic.  However, if exposed to the cryogenic liquids, they have the potential of burning skin and creating an oxygen deficient atmosphere which can lead to death.  The exposure of the hazard to the public is of minimal concern.  Reference: FESHM 4240, 5032, 5032.1, 5032.3		P: Cryogenic systems designed and reviewed by qualified personnel M: Site security plans monitor access to outside tanks M: Onsite Emergency services are provided	L: BEU C: N R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.						
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level						

#### C.6 Kinetic Energy – Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Power tools	Hazard: Personnel injury due to improper use of power tools.	L: A C: H R: I	P: Training to inform personnel on proper tool operations. P: All machine guarding required to be in place prior to use to prevent injury. P: Sharing of tool use lessons learned M: Use of PPE	L: BEU C: M R: IV
Pumps and Motors	Hazard: Personnel injury due to entrapment/entanglement.	L: A C: H R: I	P: All machine guarding required to be in place prior to use to prevent injury P: Lockout/Tagout procedure prevents personnel from accessing rotating shafts or motors. Zero energy is verified prior to equipment access. P: All areas perform hazard analysis and/or WPC process	L: BEU C: H R: III
Motion Tables	Hazard: Personnel injury due to pinch points, tip-overs, caught in between.	L: A C: H R: I	P: Lock out/ Tag out procedure prevents motor from activating P: Engineering Notes/ ORC procedure P: Safety stops P: Warning labels	L: BEU C: H R: III
Mobile Shielding	Hazard: Personnel injury due to pinch points, tip-overs, caught in between, crushing.	L: A C: H R: I	P: Securing shielding prevents tip over and pinch points P: Proper placement through hoisting/rigging with supervision P: Work control processes prevent unnecessary movement P: Spotters placed during movement	L: BEU C: H R: III

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02) U = Unlikely (1.0E-02> L >1.0E-04) EU = Extremely Unlikely (1.0E-04 > L >1.0E-06) BEU = Beyond Extremely Unlikely (1.0E-06>	eve H = M L =	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	<ul><li>I = situation</li><li>II = situation</li><li>III = situatio</li></ul>	Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern		Risk Matrix		A	Like U	lihood EU	BEU
L) Control(s) Type	~	Offsite (MOI) O	onsite-2 (co-located		Onsite-1 (facility worker)		Н	I	I	II	III
P = Preventive (reduce event occurrence		,	orker)		onsite I (memity worker)		M	II	II	III	IV
likelihood) <b>M</b> = Mitigative (reduces event consequences)	H	$C \ge Irreversible$ , other serious effects,	$C \ge Prompt \text{ wor}$ fatality or acute in		C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms			that is immediately	life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disab		threatening or permanently disabling.						
	И		C ≥ Serious injury mmediate loss of l permanent disabil nospitalization requ	ife no ities;	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C	Minor injuries; hospitalization >		Minor injuries; no hospitalization > C						
	N	Consequences less than those for Low Consequence Level	Consequences less those for Low Consequence Le	than	Consequences less than those for Low Consequence Level						

#### **Kinetic Energy – Onsite-2 Co-located Worker**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Power tools	Hazard: Personnel injury due to power tool use (flying debris, struck by object).	L: U C: H R: I	(unless trained).*	L: EU *BEU C: L R: IV
Pumps and Motors	Hazard: Personnel injury due to entrapment/entanglement.	L: U C: H R: I	P: All machine guarding required to be in place prior to use to prevent injury P: Lockout/Tagout procedure prevents personnel from accessing rotating shafts or motors. Zero energy is verified prior to equipment access P: All areas perform hazard analysis and/or WPC process M: WPC reduces consequence of co-located worker injury	L: BEU C: M R: IV
Motion Tables	Hazard: Personnel injury due to tip-overs, caught in between, crushing	L: A C: H R: I	P: Lock out/ Tag out procedure prevents the motor from activating P: Engineering Notes/ ORC procedure evaluates the tables for stability and user safety P: Safety stops (where applicable) prevent injury due to pinch points and getting caught in between events P: Warning labels provide information to prevent pinching of fingers while using motion tables	L: BEU C: H R: III
Mobile Shielding	Hazard: Personnel injury due to tip-overs, caught in between, crushing	L: A C: H R: I	P: Securing shielding prevents tip over and pinch points P: Proper placement through hoisting/rigging with supervision P: Work control processes prevent unnecessary movement P: Spotters placed during movement	L: BEU C: H R: III

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year	Co	nsequence (C, of		Risk (R, Qualitati	ve Ranking)	Risk Matrix					
$\mathbf{A} = \text{Anticipated } (L > 1.0E-02)$	eve	ent)/year		<b>I</b> = situation (event) of major concern							
U = Unlikely (1.0E-02 > L > 1.0E-04)	H :	= High		II = situation (even	t) of concern						
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate		III = situation (eve	nt) of minor concern						
06)	L=	= Low		IV = situation (ever	nt) of minimal concern				Lika	lihood	1
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	N:	= Negligible						Α	U	EU	BEU
L)							Н	ĭ	ī	п	III
Control(s) Type	С	Offsite (MOI)	Onsite-	-2 (co-located	Onsite-1 (facility worker)			1	1	11	
<b>P</b> = Preventive (reduce event occurrence			worker	r)			M	II	II	III	IV
likelihood)	H	$C \ge Irreversible$ ,	C ≥	≥ Prompt worker	$C \ge Prompt worker$	Consequences	L	III	III	IV	IV
<b>M</b> = Mitigative (reduces event consequences)		other serious effects,	fatal	ity or acute injury	fatality or acute injury		L	111	111	1 V	1 V
Acronyms		or symptoms which	that is	s immediately life-	that is immediately life-		N	IV	IV	IV	IV
<b>MOI</b> = Maximally-exposed Offsite Individual		could impair an	1	threatening or	threatening or						
		individual's ability to	perm	anently disabling.	permanently disabling.						
		take protective									
		action.									
	И	$C \ge Mild$ , transient	<b>C</b> ≥	Serious injury, no	$C \ge$ Serious injury, no						
		adverse effects.	imme	diate loss of life no	immediate loss of life no						
			perm	nanent disabilities;	permanent disabilities;						
			hospit	talization required.	hospitalization required.						
			inor injuries; no	Minor injuries; no							
		adverse effects > C		spitalization > C	hospitalization > C						

#### **Kinetic Energy – MOI Offsite**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Power tools	Hazard: N/A	L: C: R:	Public is prevented from having access to work areas	L: C: R:
Pumps and Motors	Hazard: N/A	L: C: R:	Public is prevented from having access to work areas	L: C: R:
Motion Tables	Hazard: N/A	L: C: R:	Public is prevented from having access to work areas	L: C: R:
Mobile Shielding	Hazard: N/A	L: C: R:	Public is prevented from having access to work areas	L: C: R:

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L >1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L >1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H M L	event)/year		Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern		Risk Matrix		A	Like U	elihood EU	BEU
L)		Offsita (MOI)	Onsita	-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III
Control(s) Type P = Preventive (reduce event occurrence			worke		Offsite-1 (facility worker)		M	II	II	III	IV
likelihood)  M = Mitigative (reduces event consequences)	H	$C \ge Irreversible$ , other serious effects,		≥ Prompt worker ity or acute injury	C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which		s immediately life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.		threatening or permanently disabling.							
		C ≥ Mild, transient adverse effects.  Mild, transient	imme perm hospi	nanent disabilities; talization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	adverse effects > C		inor injuries; no spitalization > C	Minor injuries; no hospitalization > C						

#### C.7 Potential Energy – Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Crane Operations	Hazard: personnel injury due to	L: A		L: BEU
	improper crane operations.	C: H		C: M
		R: I	P: Mobile Crane operators are trained and certified/licensed and take FN000360/CR.	R: IV
			P: Qualified riggers are determined by their supervisor.	
			P: All cranes are inspected on prescribed frequencies by an outside	
			vendor	
			M: Personal Protective Equipment mitigates the severity of injury by protecting the individual	
Compressed	Hazard: Personnel injury due to	L: A	P: All personnel handling compressed gasses have to take Pressure	L: BEU
		C: H	Safety orientation training FN000271	C: M
	tanks.	R: I	P: All personnel handling compressed gasses have to take compressed	R: IV
			gas cylinder safety training FN000213	
			P: All personnel must be familiar with FESHM 5000 series and apply	
			requirements	
			P: Gas cylinders are secured and capped when not in use	
			M: Personal Protective Equipment mitigates severity of injury	

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Vacuum/ Pressure Vessels/Piping	Hazard: Personnel injury due to unexpected pressure release.	L: A C: H R: I		L: BEU C: M R: IV
	Hazard: Beam pipes under vacuum	L: A C: H R: I	orientation training FN000271	L: BEU C: H R: III
Vacuum Pumps	Hazard: Personnel injury due to interaction with existing vacuum.	L: A C: H R: I	5000 series and apply requirements	L: BEU C: H R: III

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
	Hazard: Personnel injury due to			L: BEU C: M
_	1110 11110 11110	R: I		R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year	Co	nsequence (C, of	Risk (R, Qualitativ	ve Ranking)	Risk Matrix						
A = Anticipated (L > 1.0E-02)	eve	ent)/year	I = situation (event)	of major concern							
U = Unlikely (1.0E-02> L>1.0E-04)	H :	= High	II = situation (even	t) of concern							
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate	III = situation (eve	nt) of minor concern							
06)	L=	= Low	IV = situation (ever	nt) of minimal concern				Lilro	lihood		
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	<b>N</b> =	N = Negligible				Δ	II	EU	BEU		
L)						Н	I	Ţ		III	
Control(s) Type	С	Offsite (MOI) On	nsite-2 (co-located	Onsite-1 (facility worker)		П	1	1	II	111	
<b>P</b> = Preventive (reduce event occurrence		wo	orker)			M	II	II	III	IV	
likelihood)	H	$C \ge Irreversible$ ,	$C \ge Prompt worker$	$C \ge Prompt worker$	Consequences	L	III	III	IV	IV	
$\mathbf{M} = \text{Mitigative (reduces event consequences)}$			fatality or acute injury	fatality or acute injury		L	111	111	1 4	1 V	
Acronyms			hat is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
<b>MOI</b> = Maximally-exposed Offsite Individual		could impair an	threatening or	threatening or		•		•	•		
· -		individual's ability to p	ermanently disabling.	permanently disabling.							
		take protective									
		action.									
	Л	$C \ge Mild$ , transient	$C \ge Serious injury, no$	$C \ge$ Serious injury, no							
		adverse effects. in	nmediate loss of life no	immediate loss of life no							
		l r	permanent disabilities;	permanent disabilities;							
		ho	ospitalization required.	hospitalization required.							
	L	Mild, transient	Minor injuries; no	Minor injuries; no							
		adverse effects > C	hospitalization > C	hospitalization > C							
	N	Consequences less C	Consequences less than	Consequences less than	1						
		than those for Low	those for Low	those for Low							
		Consequence Level	Consequence Level	Consequence Level							

#### **Potential Energy – Onsite-2 Co-located Worker**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Crane Operations	Hazard: Struck by falling, swinging loads	L: A C: H R: I	1	L: BEU C: M R: IV
Compressed Gasses	Hazard: Collocated personnel injury due to unexpected release, or unsecure tanks	L: A C: H R: I	P: Complete New Employee ES&H Orientation, Subcontractor Orientation, New User/Affiliate Orientation, or Facility Specific	L: BEU C: H R: III
Vacuum/ Pressure Vessels	Hazard: Collocated personnel injury due to unexpected pressure release	L: A C: H R: I	P: Complete New Employee ES&H Orientation, Subcontractor Orientation, New User/Affiliate Orientation, or Facility Specific	L: BEU C: H R: III
	Hazard: Beam pipes under vacuum	L: U C: H R: I	P: Complete New Employee ES&H Orientation, Subcontractor Orientation, New User/Affiliate Orientation, or Facility Specific Hazard Awareness Training P: Beamline components go through the Operational Readiness Clearance and engineering note process with peer review and must meet applicable regulatory requirements P: System integrity verified following maintenance	L: BEU C: H R: III

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Vacuum Pumps	Hazard: Personnel injury due to interaction with existing vacuum.	L: U C: H R: I	P: Complete New Employee ES&H Orientation, Subcontractor Orientation, New User/Affiliate Orientation, or Facility Specific Hazard Awareness Training P: System integrity verified following maintenance	L: BEU C: H R: III
Material Handling	Hazard: Collocated personnel injury due to moving/handing material (rollovers, crush, etc.)		P: Complete New Employee ES&H Orientation, Subcontractor Orientation, New User/Affiliate Orientation, or Facility Specific Hazard Awareness Training P: All operators shall warn collocated personnel of a material movement evolution P: Material movements are performed by trained personnel	L: BEU C: H R: III

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.						
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level						

#### **Potential Energy – MOI Offsite**

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Crane Operations	Hazard: N/A	L: C: R:		L: C: R:
Compressed Gasses	Hazard: Injury due to unexpected release, or unsecure tanks outside of buildings	L: U C: H R: I	P: Ensure that compressed gas cylinders are properly secured while in-use P: Ensure that compressed gas cylinders are properly stored with valve protection caps in-place.	L: BEU C: H R: III
Vacuum/ Pressure Vessels	Hazard: Injury due to unexpected release, or unsecure tanks outside of buildings	L: U C: H R: I	P: All vacuum/ pressure vessels have pressure safety devices that are tested and inspected every 5 years, tracked in Fermilab pressure vessel and pressure relief device database P: All vacuum/ pressure vessels go through the Operational Readiness Clearance and engineering note process with peer review and must meet applicable regulatory requirements	L: BEU C: H R: III
Vacuum Pumps	Hazard: N/A	L: C: R:		L: C: R:
Material Handling	Hazard: N/A	L: C: R:		L: C: R:

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (even	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	<b>lihood</b> EU	BEU	
Control(s) Type P = Preventive (reduce event occurrence	С	( - )	nsite-2 (co-located orker)	Onsite-1 (facility worker)		H M	I II	I II	III	III IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible,	$C \ge Prompt worker$ fatality or acute injury	C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms MOI = Maximally-exposed Offsite Individual	onyms OI = Maximally-exposed Offsite Individual or sympto could in individual take pr		or symptoms which could impair an individual's ability to take protective action.  that is immediately lifethreatening or permanently disabling.  that is immediately lifethreatening or permanently disabling.			N	IV	IV	IV	IV	
	И	adverse effects. in	permanent disabilities;	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
		Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	V	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### C.8 Magnetic Fields – Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Fringe Fields	Hazard:  • Exposure to fringe fields beyond allowable limits (worker with ferromagnetic or electronic medical device(s))	L: A C: H R: I	P: Industrial hygiene conducts field surveys to establish safe field boundaries for workers. P: Access control points and individual components of concern (e.g., ion pumps) have postings to notify workers of magnetic hazard.	L: EU C: H R: II
	• Exposure to fringe	L: A C: L R: III	P: Industrial hygiene conducts field surveys to establish safe field boundaries for workers. P: Access control points and individual components of concern (e.g., ion pumps) have postings to notify workers of magnetic hazard.	L: EU C: L R: IV
	device(s))  • Exposure to flying metallic objects causing potential injury.  Reference: FESHM	L: A C: M R: II	P: Brass tools are used to prevent flying metallic objects from occurring, thereby preventing worker injury. P: Work Control procedure/SOP (ferromagnetic object control) requires that all ferromagnetic objects are removed prior to entry into a fringe field area (30G administrative limit). P: Work Control procedure/SOP requires worker training while in areas possessing fringe fields (300 G administrative limit).	L:_EU C: M R: III

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU	
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III	
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		1		threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### Magnetic Fields – Onsite-2 Co-located Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Fringe Fields	Hazard:  • Exposure to fringe fields beyond allowable limits (worker with ferromagnetic or electronic medical device(s))	L: A C: H R: I	P: Industrial hygiene conducts field surveys to establish safe field boundaries for workers. P: Access control points and individual components of concern (e.g., ion pumps) have postings to notify workers of magnetic hazard.	L: BEU C: H R: III
	• Exposure to fringe		P: Industrial hygiene conducts field surveys to establish safe field boundaries for workers. P: Access control points and individual components of concern (e.g., ion pumps) have postings to notify workers of magnetic hazard.	L: EU C: L R: IV
	device(s))  • Exposure to flying metallic objects causing potential injury.  Reference: FESHM	C· M	P: Brass tools are used to prevent flying metallic objects from occurring, thereby preventing worker injury. P: Work Control procedure/SOP (ferromagnetic object control) requires that all ferromagnetic objects are removed prior to entry into a fringe field area (30G administrative limit). P: Work Control procedure/SOP requires worker training while in areas possessing fringe fields (300 G administrative limit).	L:_EU C: M R: III

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU	
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III	
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		1		threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### Magnetic Fields – MOI Offsite

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Fringe Fields	Hazard:  • Exposure to fringe fields beyond allowable limits (worker with ferromagnetic or electronic medical device(s))	K: I	P: Industrial hygiene conducts field surveys to establish safe field boundaries for workers. P: Visual barriers are provided to identify extent of fringe fields, to prevent workers from accessing the hazard. P: Magnets are de-energized prior to worker entry using LO/TO procedure.	L: BEU C: H R: III
	<ul> <li>Exposure to fringe fields beyond allowable limits (worker without ferromagnetic or electronic medical device(s))</li> <li>Exposure to flying metallic objects causing potential injury.</li> <li>Reference: FESHM</li> </ul>	R: III L: U C: M	P: Industrial hygiene conducts field surveys to establish safe field boundaries for workers. P: Visual barriers are provided to identify extent of fringe fields, to prevent workers from accessing the hazard. P: Magnets are de-energized prior to worker entry using LO/TO procedure.  P: Brass tools are used to prevent flying metallic objects from occurring, thereby preventing worker injury. P: Work Control procedure/SOP (ferromagnetic object control) requires that all ferromagnetic objects are removed prior to entry into a fringe field area (30G administrative limit).	L: BEU C: L R: IV L:_BEU C: M R: IV

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (even	Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern			A	Like U	<b>lihood</b> EU	BEU	
Control(s) Type P = Preventive (reduce event occurrence	С	( - )	nsite-2 (co-located orker)	Onsite-1 (facility worker)		H M	I II	I II	III	III IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible,	C ≥ Prompt worker fatality or acute injury	C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms MOI = Maximally-exposed Offsite Individual		could impair an	hat is immediately life- threatening or permanently disabling.	that is immediately life- threatening or permanently disabling.	N		IV	IV	IV	IV	
	И	adverse effects. in	permanent disabilities;	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
		Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	V	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### C.9 Other hazards – Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Confined Spaces	Hazard:	L: A C: H R: I	P: Training P: Work practice procedure (attendant) P: Permit required Permit and reclassification permit (ESH involvement) P: atmospheric monitoring M: mechanical ventilation when required M: PPE, harness, tripod, etc. when required	L: BEU C: H R: III
Noise	Hazard:  • Exposure above OELs via use of machinery, tools, co- location w/ equipment etc.	L: A C: L R: III	P: Hearing Conservation Training P: Equipment isolation M: Engineering controls (isolation, sound barriers) M: PPE (HPDs) M: IH Surveys and follow up w/ workers-administrative controls M: Hearing Conservation Program	L: EU C: N R: IV
Silica	Reference: FESHM 4140  Hazard:  • Airborne exposure above OEL via concrete (or similar material) machining, moving dirt or gravel	L: A C: H R: I	P: Silica Awareness Training, Respiratory Protection Training P: Work Planning (HA, SOP) M: Engineering Controls (HEPA, wet method) M: PPE (respirator, PAPR)	L: EU C: L R: IV
Ergonomics	Reference: FESHM 4195  Hazard:  Office space Industrial space (over lifting, repetitive motion, static posture)  Reference: FESHM 4120	L: A C: H R: I	P: Ergo assessment (ESH SME) P: Training (Back works, office ergo) P: Work planning (HA, prescribed techniques, etc.) M: Administrative Controls, i.e. Lifting techniques, office ergo techniques (stand, sit, 20 min breaks, etc)	L: BEU C: M R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Asbestos	Hazard:	L: A	P: Asbestos Management Plan (FESHM)	L: EU
	<ul> <li>Deteriorating</li> </ul>	C: H	P: building material sampling (licensed)	C: L
	building materials	R: I	M: Building walkthroughs (AFMSs, ESH SMEs, etc.) M: Abatement	R: IV
	Reference: FESHM 4180			
Working at	Hazard:	L: A	P: Fall protection program	L: EU
Heights	• Falls, dropped	C: H	P: Training for scaffolding, ladders, mobile elevating work	C: M
8	tools/material	R: I	platforms P: Guard rails	R: III
	Reference: FESHM 7060, 7070		M: PPE-PFAS including approved anchor points, hard hats	

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H : M L :	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (event	Risk (R, Qualitative Ranking) I = situation (event) of major concern II = situation (event) of concern III = situation (event) of minor concern IV = situation (event) of minimal concern			A	Like U	lihood EU	BEU	
L) Control(s) Type	C	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)	-	Н	I	I	П	III	
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	П	П	III	IV	
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms		or symptoms which t	that is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		1		threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### Other hazards - Onsite-2 Co-located Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Confined Spaces	Hazard:  • Toxic atmosphere • Accidental entry  Reference: FESHM	L: BEU C: H R: III	P: Work practice procedure (attendant performs warning) P: atmospheric monitoring M: mechanical ventilation M: physical barriers, signage	L: BEU C: L R: IV
Noise	Hazard:  • Exposure above OELs via use of machinery, tools, co- location w/ equipment, etc.	L: A C: L R: III	M: Engineering controls (isolation, sound barriers) M: PPE (HPDs) P: Hearing Conservation Training P: IH Surveys and follow up w/ workers P: Equipment isolation	L: BEU C: N R: IV
Silica	Reference: FESHM  Hazard:  • Airborne exposure above OEL via concrete (or similar material) machining, moving dirt or gravel	L: A C: H R: I	P: Work Planning (HA, SOP) P: Work oversite (Work planner, ESH) M: Engineering Controls (HEPA, wet method)	L: EU C: M R: III
Ergonomics	Reference: FESHM Hazard: N/A	L: C: R:		L: C: R:
Asbestos	Hazard: • Deteriorating building materials	L: A C: H R: I	P: Asbestos Management Plan (FESHM) P: building material sampling (licensed) M: Building walkthroughs (AFMSs, ESH SMEs, etc.) M: Abatement	L: EU C: L R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Working at	Hazard:	L: A	P: Fall protection program	L: EU
Heights	Struck by dropped	C: H	P: Work planning	C: M
		R: I	M: PPE-hard hats	R: III
	Reference: FESHM			

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year	Co	nsequence (C, of	Risk	(R, Qualitativ	Risk Matrix						
A = Anticipated (L > 1.0E-02)	event)/year			I = situation (event) of major concern							
U = Unlikely (1.0E-02 > L > 1.0E-04)		= High	$\mathbf{H} = \mathbf{H}$	II = situation (event) of concern							
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate	III =	situation (ever							
06)	L:	= Low	IV =	<b>IV</b> = situation (event) of minimal concern					Like	lihood	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	$\mathbf{N} = $ Negligible						A	U	EU	BEU	
L)							Н	T	I	II	III
Control(s) Type			,	2 (co-located Onsite-1 (facility worker)				1	1		
<b>P</b> = Preventive (reduce event occurrence			worker)				M	II	II	III	IV
likelihood)		$C \ge Irreversible$ ,		mpt worker	$C \ge Prompt worker$	Consequences	T.	III	III	IV	IV
<b>M</b> = Mitigative (reduces event consequences)		other serious effects,	•	r acute injury	fatality or acute injury	_		111	111	1,	- 1 1
Acronyms		or symptoms which		nediately life-	that is immediately life-		N	IV	IV	IV	IV
<b>MOI</b> = Maximally-exposed Offsite Individual	could impair an			reatening or threatening or permanently disabling.							
		take protective									
		action.									
	И	$C \ge Mild$ , transient		ous injury, no	$C \ge$ Serious injury, no						
		adverse effects.	immediate	loss of life no	immediate loss of life no						
			permanen	nt disabilities;	permanent disabilities;						
			hospitaliza	tion required.	hospitalization required.						
	L	Mild, transient	Minor i	injuries; no	Minor injuries; no						
		adverse effects > C	hospitali	ization > C	hospitalization > C						
	N	Consequences less	Conseque	nces less than	Consequences less than						
		than those for Low	those	for Low	those for Low						
		Consequence Level	Consequ	ience Level	Consequence Level						

#### Other hazards – MOI Offsite

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Confined Spaces	Hazard:  • Toxic atmosphere • Accidental entry  Reference: FESHM	L: BEU C: H R: III	P: Work practice procedure (attendant performs warning) P: atmospheric monitoring M: mechanical ventilation M: physical barriers	L: BEU C: L R: IV
Noise	Hazard:  • Exposure above OELs via use of machinery, tools, co- location w/ equipment, etc.	L: A C: N R: IV	No further analysis required	L: A C: N R: IV
Silica	Reference: FESHM  Hazard:  • Airborne exposure above OEL via concrete (or similar material) machining, moving dirt or gravel  Reference: FESHM	L: A C: H R: I	P: Work Planning (HA, SOP) P: Work oversite (Work planner, ESH) M: Engineering Controls (HEPA, wet method)	L: EU C: M R: III
Ergonomics	Hazard: N/A	L: C: R:		L: C: R:
Asbestos	Hazard: N/A	L: C: R:		L: C: R:

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Working at	Hazard:	L: A	P: Fall protection program	L: EU
Heights	<ul> <li>Struck by dropped</li> </ul>	C: H	P: Work planning	C: M
		R: I	P: Construction Barriers prevent public access to this hazard.	R: III
	Reference: FESHM			

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-04)	eve H :	nsequence (C, of ent)/year = High = Moderate	$\mathbf{I} = \mathbf{s}$ $\mathbf{II} = \mathbf{s}$	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern		Risk Matrix					
06)	L =			IV = situation (event) of minimal concern				A	Like U	lihood EU	BEU
L) Control(s) Type P = Preventive (reduce event occurrence	С	,	Onsite-2 (co- vorker)	o-located	Onsite-1 (facility worker)		H M	I	I	III	III IV
likelihood)  M = Mitigative (reduces event consequences)	H	C ≥ Irreversible, other serious effects,	C ≥ Pro	ompt worker r acute injury	C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms MOI = Maximally-exposed Offsite Individual		could impair an	threat	mediately life- itening or itly disabling.	that is immediately life- threatening or permanently disabling.		N	IV	IV	IV	IV
	И		immediate permanen	nt disabilities;	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	L	Mild, transient adverse effects > C		injuries; no lization > C	Minor injuries; no hospitalization > C						
	V	Consequences less than those for Low Consequence Level	those	ences less than e for Low uence Level	Consequences less than those for Low Consequence Level						

#### C.10 Access & Egress – Onsite-1 Facility Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Egress	A blocked egress would be of major life safety concern.  An egress might be blocked due to construction work, poor housekeeping, or faulty doors.  In the event of a fire or other lifethreatening event, a blocked egress would be life threatening.	C: H R: I	II. 1791CSS Daulways ale cically mained	C: N R: IV
	The exposure of the hazard to the facility worker is of major concern.  Reference: FESHM 6010		hydrants, throughout the complex M: Egress stairways are constructed as fire barriers	

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L >1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L >1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H = M L =	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (eve II = situation (eve III = situation (eve	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	elihood EU	BEU
L) Control(s) Type	С	Offsite (MOI) O	Onsite-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III
<b>P</b> = Preventive (reduce event occurrence	Ĺ	w	orker)			M	II	II	III	IV
likelihood) <b>M</b> = Mitigative (reduces event consequences)	Н	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$ fatality or acute injury	$C \ge Prompt worker$ fatality or acute injury	Consequences	L	III	III	IV	IV
Acronyms		or symptoms which t	that is immediately life	- that is immediately life-		N	IV	IV	IV	IV
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.						
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life n permanent disabilities nospitalization required	o immediate loss of life no permanent disabilities;						
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C						
	N	Consequences less than those for Low Consequence Level	Consequences less that those for Low Consequence Level	•						

#### Access & Egress – Onsite-2 Co-located Worker

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Egress	major life safety concern.	R: II	P: Egress pathways are clearly marked P: Exit signs and emergency lighting is present P: Fire Safety and Life Safety Inspections are performed Fire Protection Group and the Fire Department.	C: N R: IV
	major life safety concern.  An egress might be blocked due to construction work, poor		P: Fire Safety and Life Safety Inspections are performed Fire Protection Group and the Fire Department. P: Life safety systems testing is performed at prescribed	
housekeeping, or faulty door In the event of a fire, a block	housekeeping, or faulty doors.  In the event of a fire, a blocked egress would be life threatening.		frequencies M: Life safety systems are monitored by a sitewide monitoring system with notification to the emergency dispatch center that is constantly staffed, 24/7, 365 days M: Fire detection and/or suppression is present	
	The exposure of the hazard to the co-located worker is of concern.  Reference: FESHM 6010		M: Manual fire suppression services are provided, i.e., fire hydrants, throughout the complex M: Egress stairways are constructed as fire barriers	

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L >1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L >1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	eve H = M L =	nsequence (C, of ent)/year = High = Moderate = Low = Negligible	I = situation (event II = situation (even III = situation (eve	Risk (R, Qualitative Ranking)  I = situation (event) of major concern  II = situation (event) of concern  III = situation (event) of minor concern  IV = situation (event) of minimal concern			A	Like U	<b>lihood</b> EU	BEU	
Control(s) Type	7	Offsite (MOI)	onsite-2 (co-located	Onsite-1 (facility worker)		Н	I	I	II	III	
P = Preventive (reduce event occurrence		,	orker)	onsite I (incline, worner)	_	M	II	П	III	IV	
likelihood) <b>M</b> = Mitigative (reduces event consequences)	H	$C \ge Irreversible$ , other serious effects,	$C \ge Prompt worker$ fatality or acute injury	C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV	
Acronyms			that is immediately life-	that is immediately life-		N	IV	IV	IV	IV	
MOI = Maximally-exposed Offsite Individual		could impair an individual's ability to take protective action.	threatening or permanently disabling.	threatening or permanently disabling.							
	И	adverse effects.	C ≥ Serious injury, no mmediate loss of life no permanent disabilities; nospitalization required.	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.							
	L	Mild, transient adverse effects > C	Minor injuries; no hospitalization > C	Minor injuries; no hospitalization > C							
	7	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level	Consequences less than those for Low Consequence Level							

#### Access & Egress – MOI Offsite

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Life Safety Egress	Hazard: N/A	L: C R:		L: C: R:
	Reference: FESHM 6010			

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.										
Likelihood (L, of event)/year	Co	onsequence (C, of	Risk (R, Qualitativ		Risk Matrix					
$\mathbf{A} = \text{Anticipated } (L > 1.0\text{E-}02)$	ev	ent)/year	I = situation (event)	<b>I</b> = situation (event) of major concern						
U = Unlikely (1.0E-02> L > 1.0E-04)		= High	$\mathbf{H} = \text{situation (even)}$							
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-	M	= Moderate	III = situation (ever	III = situation (event) of minor concern						
06)	L:	= Low	IV = situation (ever	<b>IV</b> = situation (event) of minimal concern				Like	lihood	
<b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	N:	= Negligible					A	U	EU	BEU
L)						Н	T	ī	II	III
Control(s) Type	С		site-2 (co-located	Onsite-1 (facility worker)			1	1		
<b>P</b> = Preventive (reduce event occurrence			rker)			M	II	II	III	IV
likelihood)	H	C ≥ Irreversible, other serious effects,	$C \ge Prompt worker$	C ≥ Prompt worker	Consequences	L	III	III	IV	IV
M = Mitigative (reduces event consequences)		/	fatality or acute injury nat is immediately life-	fatality or acute injury that is immediately life-		M	IV	IV	137	IV
Acronyms		could impair an	threatening or	threatening or		N	1 V	IV	IV	IV
MOI = Maximally-exposed Offsite Individual			ermanently disabling.	permanently disabling.						
		take protective	ermanently disabiling.	permanentry disabiling.						
		action.								
	<b>I</b>		C ≥ Serious injury, no	C > C - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 -	-					
	V1			C ≥ Serious injury, no immediate loss of life no						
			permanent disabilities;	permanent disabilities;						
	F			hospitalization required.	-					
	L	Mild, transient	Minor injuries; no	Minor injuries; no						
	<u> </u>	adverse effects > C	hospitalization > C	hospitalization > C						
	N		Consequences less than	Consequences less than						
		than those for Low	those for Low	those for Low						
		Consequence Level	Consequence Level	Consequence Level						

#### **C.11** Environmental

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Airborne	radionuclides beyond permitted limits	C: N R: IV	identify potential airborne releases of radionuclides so measures to prevent releases are engineered into new facilities.  P: Facility designed to confine airborne release at the designated release point  M: Facility designed ventilation to delay airborne release to reduce emission of short half-lived radionuclides  M: Facility designed ventilation stack heights, stack locations, and ventilation flow rates to reduce potential doses from radionuclides  M: Continuous monitoring of radiological stacks is performed for primary facilities where airborne radionuclides are released and periodic measurements at and around other release points are taken and shared with the facilities so that information can be used to improve operations and mitigate releases.  M: Weekly review of year-to-date emissions by a Radiation Physicist  M: Administrative controls specified in FESHM/FRCM, Environmental Monitoring Plan, and Environmental Radiological Protection Program.	L: EU C: N R: IV
	chemicals beyond permitted limits (Consequences based on Onsite Worker qualitative consequence matrix)	C: N R: IV	contain emission controls to reduce content P: Generators only operate when needed or for a short period during monthly PM activities. M: Tracking of emissions sources	C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Water	Discharge of radionuclides into onsite waters beyond permitted limits		identify potential surface water impacts, so that engineering	L: U C: N R: IV
	Discharge of chemicals into onsite waters beyond permitted limits     (Consequence based on Onsite worker qualitative consequence matrix)  Reference: FESHM 8000 series	L: A C: H R: I	purpose of preventing future releases.	L: U C: N R: IV

Hazard	Hazard Description	Baseline Qualitative Risk (without controls)	Preventative (P)/ Mitigative (M)	Residual Qualitative Risk (with controls)
Soil	beam loss areas beyond allowable concentrations of radionuclides above Fermilab limits  • Discharge of chemicals into onsite soils beyond RCRA limits	L: A C: N R: IV L: A C: H R: I	identify potential soil activation and groundwater impacts so measures to prevent beam loss are engineered into new facilities.  P: Review of excavation and digging across site and monitoring of soil prior to project commencement prevents uncontrolled spread of radioactive soil.  P: Requirements for digging the soil near beam enclosures, target stations and beam absorber, to protect against erosion, prevent contaminant spread, and return the likely activated soil back to its original depth.  M: Decontamination or soil removal mitigates spread of contamination if limits are exceeded  M: Administrative controls specified in FESHM/FRCM,	L: BEU C: N R: IV L: EU C: L R: IV

Radiological Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year	Consequence (C, of		Risk (R, Qualitati	Risk Matrix							
A = Anticipated (L > 1.0E-02)	even	t)/year	I = situation (event)	I = situation (event) of major concern				Like	lihood		
U = Unlikely (1.0E-02> L > 1.0E-04)	$\mathbf{H} = \mathbf{I}$	High	II = situation (even	<b>II</b> = situation (event) of concern			Α	U	EU	BEU	
EU = Extremely Unlikely (1.0E-04 > L > 1.0E-		Moderate		<b>III</b> = situation (event) of minor concern		Н	I	I	II	III	
06) <b>BEU</b> = Beyond Extremely Unlikely (1.0E-06>	L = I N = I	Low Negligible	IV = situation (even)	IV = situation (event) of minimal concern			II	II	III	IV	
L)	,	regrigiote				L	III	III	IV	IV	
Control(s) Type P = Preventive (reduce event occurrence	C	0115100 (1.101)	Onsite-2 (co-located worker)	Onsite-1 (facility worker)		N	IV	IV	IV	IV	
likelihood)	H	C ≥ 25.0 rem	<b>C</b> ≥ 100 rem	<b>C</b> ≥ 100 rem							
<b>M</b> = Mitigative (reduces event consequences)	M	25.0 rem > $\mathbb{C} \ge 5$	$100 \text{ rem} > \mathbb{C} \ge 25 \text{ rem}$	$100 \text{ rem} > \mathbb{C} \ge 25 \text{ rem}$							
Acronyms		rem									
<b>MOI</b> = Maximally-exposed Offsite Individual	L	5 rem > <b>C</b>	25 rem > C	25 rem > C							
rem = Roentgen equivalent man	N	0.5 rem > <b>C</b>	5 rem > C	5 rem > C							

Other Hazard Consequences, derived from Figure C-1, "Example Qualitative Consequence Matrix", DOE-HDBK-1163-2020.											
Likelihood (L, of event)/year  A = Anticipated (L > 1.0E-02)  U = Unlikely (1.0E-02> L > 1.0E-04)  EU = Extremely Unlikely (1.0E-04 > L > 1.0E-06)  BEU = Beyond Extremely Unlikely (1.0E-06>	$\mathbf{L} = \mathbf{Low}$			Risk (R, Qualitativ I = situation (event) II = situation (even III = situation (even IV = situation (even	Risk Matrix  Likelihood  A U EU BEU						
Control(s) Type P = Preventive (reduce event occurrence	(reduce event occurrence  (reduces event consequences)  ally-exposed Offsite Individual  ally-exposed Offsite Individual  take protective action.  worl  C ≥ Irreversible, other serious effects, or symptoms which could impair an individual's ability to take protective action.	0 ( 0 -)	Onsite- worker	`	Onsite-1 (facility worker)	-	H M	I	I	III	III IV
likelihood)  M = Mitigative (reduces event consequences)  Acronyms  MOI = Maximally-exposed Offsite Individual			C ≥ Prompt worker rality or acute injury	C ≥ Prompt worker fatality or acute injury	Consequences	L	III	III	IV	IV	
		could impair an individual's ability to take protective	t	is immediately life- threatening or nanently disabling.	that is immediately life- threatening or permanently disabling.		N	IV	IV	IV	IV
	Л	C ≥ Mild, transient adverse effects.	immed perm	nanent disabilities;	C ≥ Serious injury, no immediate loss of life no permanent disabilities; hospitalization required.						
	Ĺ	Mild, transient adverse effects > C		inor injuries; no spitalization > C	Minor injuries; no hospitalization > C						
	Ŋ	Consequences less than those for Low Consequence Level	ť	equences less than those for Low asequence Level	Consequences less than those for Low Consequence Level						